



**AUXILIARIES FOR PUBLIC LIGHTING
-LIST OF APPROVED LED-DRIVERS-**

1. Introduction

This document presents the list of auxiliaries for LED light sources for public lightingstreet lighting approved by SYNERGRID Commission 4.

Approval was based on the compliance of the auxiliaries with the conditions described in document: C4-10.2 "Spécification technique 005 équipements d'éclairage public - Prescriptions relatives aux auxiliaires pour sources lumineuses LED" in French and "Technische specificatie 005 voor uitrustingen voor openbare verlichting – Voorschriften met betrekking tot de voorschakelapparatuur van ledverlichting" in Dutch version 02/2020 or later.

Competent committee	CE4
Functional mailbox	n/a
Indicative / restrictive	Restrictif
Updated on:	21.01.2025

2. List of approved LED drivers

Update :01/2025

Reference	Manufacturer	Model	Article number	Supply power standby	Output power in the operating window	DC voltage output	DC output current	Certification DALI Alliance	Date of approval	Validity
SYN_CE421031	Inventronics	EBS-025S045BT2		0.44 W	10 W - 25 W	28 V - 84 V	120 mA - 450 mA	D4i (Internal DALI)	10/05/2023	10/05/2028
SYN_CE421031	Inventronics	EBS-025S070BT2		0.34 W	10 W - 25 W	18 V - 56 V	180 mA - 700 mA	D4i (Internal DALI)	10/05/2023	10/05/2028
SYN_CE421031	Inventronics	EBS-025S105BT2		0.34 W	10 W - 25 W	12 V - 36 V	280 mA - 1050 mA	D4i (Internal DALI)	10/05/2023	10/05/2028
SYN_CE421031	Inventronics	EBS-120S070BT2		0.45 W	36 W - 120 W	86 V - 266 V	135 mA - 700 mA	D4i (Internal DALI)	10/05/2023	10/05/2028
SYN_CE421031	Inventronics	EBS-120S105BT2		0.41 W	36 W - 120 W	57 V - 171 V	210 mA - 1050 mA	D4i (Internal DALI)	10/05/2023	10/05/2028
SYN_CE421031	Inventronics	EBS-120S150BT2		0.79 W	36 W - 120 W	40 V - 114 V	320 mA - 1500 mA	D4i (Internal DALI)	10/05/2023	10/05/2028
SYN_CE421031	Inventronics	EBS-165S070BT2		0.33 W	50 W - 165 W	118 V - 367 V	135 mA - 700 mA	D4i (Internal DALI)	10/05/2023	10/05/2028
SYN_CE421031	Inventronics	EBS-165S105BT2		0.45 W	50 W - 165 W	79 V - 236 V	210 mA - 1050 mA	D4i (Internal DALI)	10/05/2023	10/05/2028
SYN_CE421031	Inventronics	EBS-165S150BT2		0.43 W	50 W - 165 W	55 V - 157 V	320 mA - 1500 mA	D4i (Internal DALI)	10/05/2023	10/05/2028
SYN_CE421031	Inventronics	EBS-040S045BT2		0.41 W	12 W - 40 W	44 V - 133 V	90 mA - 450 mA	D4i (Internal DALI)	15/11/2021	15/11/2026
SYN_CE421031	Inventronics	EBS-040S070BT2		0.45 W	12 W - 40 W	28 V - 89 V	130 mA - 700 mA	D4i (Internal DALI)	15/11/2021	15/11/2026
SYN_CE421031	Inventronics	EBS-040S105BT2		0.41 W	12 W - 40 W	19 V - 57 V	210 mA - 1050 mA	D4i (Internal DALI)	15/11/2021	15/11/2026
SYN_CE421031	Inventronics	EBS-080S070BT2		0.41 W	30 W - 80 W	57 V - 178 V	170 mA - 700 mA	D4i (Internal DALI)	15/11/2021	15/11/2026
SYN_CE421031	Inventronics	EBS-080S105BT2		0.38 W	30 W - 80 W	38 V - 114 V	260 mA - 1050 mA	D4i (Internal DALI)	15/11/2021	15/11/2026

SYN_CE421031	Inventronics	EBS-080S150BT2		0.45 W	30 W - 80 W	27 V - 76 V	390 mA - 1500 mA	D4i (Internal DALI)	15/11/2021	15/11/2026
SYN_CE421026	Osram	OT DX 40/220-240/1A0 DIMA LT2 E		0.48 W	8 W - 40 W	15 V - 56 V	200 - 1050 mA	D4i Alliance Certification	13/10/2021	13/10/2026
SYN_CE421027	Osram	OT DX 75/220-240/1A0 DIMA LT2 E		0.48 W	16 W - 75 W	35 V - 115 V	200 - 1050 mA	D4i Alliance Certification	13/10/2021	13/10/2026
SYN_CE421028	Osram	OT DX 110/220-240/1A0 DIMA LT2 E		0.48 W	35 W - 110 W	77 V - 220 V	200 - 1050 mA	D4i Alliance Certification	13/10/2021	13/10/2026
SYN_CE421029	Osram	OT DX 165/220-240/1A0 DIMA LT2 E		0.48 W	26 W - 165 W	130 V - 260 V	200 - 1050 mA	D4i Alliance Certification	13/10/2021	13/10/2026
SYN_CE423015	Signify	Xi SR 22W 0.2-1.0A SNEMP 230V C123 sXt	929002952406	0.3 W	6 W - 22 W	8 V - 48 V	200 mA - 1050 mA	D4i (Internal DALI)	27/10/2023	27/10/2028
SYN_CE423015	Signify	Xi SR 40W 0.2-1.0A SNEMP 230V C123 sXt	929002952506	0.3 W	11 W - 40 W	20 V - 77 V	200 mA - 1050 mA	D4i (Internal DALI)	27/10/2023	27/10/2028
SYN_CE422012	Signify	Philips Xi SR 165W 0.2-1.0A SNEMP 230V C170 sXt	929003389606	0.33 W	16 W - 165 W	80 V - 300 V	200 mA - 1050 mA	D4i (Internal DALI)	06/07/2023	06/07/2028
SYN_CE422007	Signify	Xi SR 75W 2 0.3-1.0A SNEMPF C170 sXt	929002827206	0.30 W	22,5 W - 75 W	35 V - 108 V	300 - 1050 mA	D4i (Internal DALI)	27/06/2023	27/06/2028
SYN_CE422007	Signify	Xi SR 75W 0.2-1.0A SNEMP 230V C150 sXt	929002859506	0.30 W	21 W - 75 W	35 V - 1050 V	200 - 1050 mA	D4i (Internal DALI)	27/06/2023	27/06/2028
SYN_CE422007	Signify	Xi SR 110W 0.2-1.0A SNEMP 230V C150 sXt	929002859606	0.30 W	32 W - 110 W	50 V - 220 V	200 - 1050 mA	D4i (Internal DALI)	27/06/2023	27/06/2028
SYN_CE420011	Signify	Philips Xi FP 110W 0.2-0.7A SNLDAE 230V C133 sXt	929002873106	< 0,5 W	31 W - 110 W	70 - 220 Vdc	200 - 700 mA	DALI2 (External DALI)	18/08/2021	18/08/2026
SYN_CE420011	Signify	Philips Xi FP 110W 0.3-1.0A SNLDAE 230V C133 sXt	929002873206	< 0,5 W	31 W - 110 W	50 - 160 Vdc	300 - 1050 mA	DALI2 (External DALI)	18/08/2021	18/08/2026
SYN_CE420011	Signify	Philips Xi FP 75W 0.2-0.7A SNLDAE 230V C133 sXt	929002872806	< 0,5 W	22 W - 75 W	50 - 150 Vdc	200 - 700 mA	DALI2 (External DALI)	18/08/2021	18/08/2026
SYN_CE420011	Signify	Philips Xi FP 75W 0.3-1.0A SNLDAE 230V C133 sXt	929002872906	< 0,5 W	22 W - 75 W	35 - 108 Vdc	300 - 1050 mA	DALI2 (External DALI)	18/08/2021	18/08/2026

SYN_CE420011	Signify	Philips Xi FP 75W 0.5-1.5A SNLDAE 230V C133 sXt	929002873006	< 0,5 W	22 W - 75 W	25 - 71 Vdc	500 - 1500 mA	DALI2 (External DALI)	18/08/2021	18/08/2026
SYN_CE420011	Signify	Philips Xi FP 150W 0.2-0.7A SNLDAE 230V S240 sXt	929002128606 929003458206	< 0,5 W	45 W - 150 W	90 - 283 Vdc	200 - 700 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 150W 0.3-1.0A SNLDAE 230V S240 sXt	929002128706 929003458506	< 0,5 W	45 W - 150 W	70 - 214 Vdc	300 - 1050 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 165W 0.2-0.7A SNLDAE 230V C170 sXt	929000976206	< 0,5 W	47 W - 165 W	100 - 300 Vdc	200 - 700 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 165W 0.3-1.0A SNLDAE 230V C170 sXt	929000976306	< 0,5 W	47 W - 165 W	80 - 235 Vdc	300 - 1050 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 22W 0.2-0.7A SNLDAE 230V C123 sXt	929002165006	< 0,5 W	6 W - 22 W	16 - 48 Vdc	200 - 700 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 22W 0.2-0.7A SNLDAE 230V S175 sXt	929002172306	< 0,5 W	6 W - 22 W	16 - 48 Vdc	200 - 700 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 22W 0.3-1.0A SNLDAE 230V C123 sXt	929002165106	< 0,5 W	6 W - 22 W	8 - 32 Vdc	300 - 1050 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 22W 0.3-1.0A SNLDAE 230V S175 sXt	929002172406 929003458706	< 0,5 W	6 W - 22 W	8 - 32 Vdc	300 - 1050 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 330W 2:0.2-0.75A SNDAE 230V C240 sXt	929002114806	< 0,5 W	110 W - 330 W	100 - 300 Vdc	200 - 750 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 40W 0.2-0.7A SNLDAE 230V C123 sXt	929002165206	< 0,5 W	12 W - 40 W	25 - 77 Vdc	200 - 700 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 40W 0.2-0.7A SNLDAE 230V S175 sXt	929002128306 929003458606	< 0,5 W	12 W - 40 W	25 - 77 Vdc	200 - 700 mA	DALI2 (External DALI)	26/01/2021	26/01/2026

SYN_CE420011	Signify	Philips Xi FP 40W 0.3-1.0A SNLDAE 230V C123 sXt	929002165306	< 0,5 W	12 W - 40 W	20 - 54 Vdc	300 - 1050 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 40W 0.3-1.0A SNLDAE 230V S175 sXt	929002172506 929003458806	< 0,5 W	12 W - 40 W	20 - 54 Vdc	300 - 1050 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 75W 0.2-0.7A SNLDAE 230V S240 sXt	929002128406 929003458306	< 0,5 W	22 W - 75 W	50 - 150 Vdc	200 - 700 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420011	Signify	Philips Xi FP 75W 0.3-1.0A SNLDAE 230V S240 sXt	929002128506 929003458406	< 0,5 W	22 W - 75 W	35 - 108 Vdc	300 - 1050 mA	DALI2 (External DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 110W 0.2-0.7A SNEMP 230V C150 sXt	929002808606	< 0,5 W	32 W - 110 W	70 - 220 Vdc	200 - 700 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 110W 0.3-1.0A SNEMP 230V C150 sXt	929002808706	< 0,5 W	32 W - 110 W	50 - 160 Vdc	300 - 1050 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 150W 0.2-0.7A SNEMP 230V S240 sXt	929002172106	< 0,5 W	45 W - 150 W	90 - 283 Vdc	200 - 700 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 150W 0.3-1.0A SNEMP 230V S240 sXt	929002172206	< 0,5 W	45 W - 150 W	90 - 214 Vdc	300 - 1050 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 22W 0.2-0.7A SNEMP 230V C133 sXt	929002178806	< 0,5 W	6 W - 22 W	25 - 77 Vdc	200 - 700 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 22W 0.3-1.0A SNEMP 230V C133 sXt	929002178906	< 0,5 W	6 W - 22 W	8 - 32 Vdc	300 - 1050 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 40W 0.2-0.7A SNEMP 230V C133 sXt	929002179006	< 0,5 W	11 W - 40 W	25 - 77 Vdc	200 - 700 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 40W 0.3-1.0A SNEMP 230V C133 sXt	929002179106	< 0,5 W	11 W - 40 W	20 - 54 Vdc	300 - 1050 mA	D4I (Internal DALI)	26/01/2021	26/01/2026

SYN_CE420012	Signify	Philips Xi SR 75W 0.2-0.7A SNEMP 230V C150 sXt	929002808406	< 0,5 W	21 W - 75 W	50 - 150 Vdc	200 - 700 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 75W 0.2-0.7A SNEMP 230V S240 sXt	929002171906	< 0,5 W	22 W - 75 W	50 - 150 Vdc	200 - 700 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 75W 0.3-1.0A SNEMP 230V C150 sXt	929002808506	< 0,5 W	21 W - 75 W	35 - 108 Vdc	300 - 1050 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420012	Signify	Philips Xi SR 75W 0.3-1.0A SNEMP 230V S240 sXt	929002172006	< 0,5 W	22 W - 75 W	35 - 108 Vdc	300 - 1050 mA	D4I (Internal DALI)	26/01/2021	26/01/2026
SYN_CE420026	Tridonic	EXC OTD LCO 14/100-500/38 o4a NF C EXC3	28003165; 87500707	0.33 W	2,24 W - 14 W	12 V - 38 V	100 mA - 550 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 24/200-1050/39 o4a NF C EXC3	28003166; 87500708 (Low voltage)	0.27 W	3,84 W - 24 W	11 V - 23 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 24/200-1050/39 o4a NF C EXC3	28003166; 87500708 (high voltage)	0.27 W	3,84 W - 24 W	19 V - 39 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 40/200-1050/64 o4a NF C EXC3	28003167; 87500709 (Low voltage)	0.27 W	6,4 W - 40 W	18 v - 38 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 40/200-1050/64 o4a NF C EXC3	28003167; 87500709 (High voltage)	0.28 W	6,4 W - 40 W	30 V - 64 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 60/200-1050/100 o4a NF C EXC3	28003168; 87500710 (Low voltage)	0.27 W	9,6 W - 60 W	28 V - 59 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 60/200-1050/100 o4a NF C EXC3	28003168; 87500710 (High voltage)	0.27 W	9,6 W - 60 W	47 V - 100 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 90/200-1050/165 o4a NF C EXC3	28003162; 87500717 (Low voltage)	0.30 W	14,4 W - 90 W	46 V - 97 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 90/200-1050/165 o4a NF C EXC3	28003162; 87500717 (High voltage)	0.31 W	15,6 W - 90 W	78 V - 165 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 135/200-1050/220 o4a NF C EXC3	28003163; 87500716 (Low voltage)	0.29 W	26,2 W - 135 W	62 V - 131 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 135/200-1050/220 o4a NF C EXC3	28003163; 87500716 (High voltage)	0.29 W	27 W - 135 W	104 V - 220 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026

SYN_CE420026	Tridonic	EXC OTD LCO 200/200-1050/355 o4a NF C EXC3	28003164; 87500711 (Low voltage)	0.27 W	31,9 W - 200 W	100 V - 211 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420026	Tridonic	EXC OTD LCO 200/200-1050/355 o4a NF C EXC3	28003164; 87500711 (High voltage)	0.29 W	33,5 W - 200 W	169 V - 355 V	200 mA - 1050 mA	DALI2 (External DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 14/100-550/38 pD+ NF C PRE3	87500828	0.33 W	2,24 W - 14 W	12 V - 38 V	100 mA - 550 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 24/200-1050/39 pD+ NF C PRE3	87500829 (Low voltage)	0.27 W	3.84 W - 24 W	11 V - 23 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 24/200-1050/39 pD+ NF C PRE3	87500829 (High voltage)	0.27 W	3.84 W - 24 W	19 V - 39 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 40/200-1050/64 pD+ NF C PRE3	87500830 (Low voltage)	0.27 W	6.4 W - 40 W	18 V - 38 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 40/200-1050/64 pD+ NF C PRE3	87500830 (High voltage)	0.28 W	6.4 W - 40 W	30 V - 64 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 60/200-1050/100 pD+ NF C PRE3	87500831 (Low voltage)	0.27 W	9.6 W - 60 W	28 V - 59 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 60/200-1050/100 pD+ NF C PRE3	87500831 (High voltage)	0.27 W	9.6 W - 60 W	47 V - 100 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 90/200-1050/165 pD+ NF C PRE3	87500832 (Low voltage)	0.30 W	14.4 W - 90 W	46 V - 97 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 90/200-1050/165 pD+ NF C PRE3	87500832 (High voltage)	0.31 W	15.6 W - 90 W	78 V - 165 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 135/200-1050/220 pD+ NF C PRE3	87500833 (Low voltage)	0.29 W	26.2 W - 135 W	62 V - 131 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 135/200-1050/220 pD+ NF C PRE3	87500833 (High voltage)	0.29 W	27 W - 135 W	104 V - 220 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 200/200-1050/355 pD+ NF C PRE3	87500834 (Low voltage)	0.27 W	31.9 W - 200 W	100 V - 211 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026
SYN_CE420027	Tridonic	PRE OTD LCO 200/200-1050/355 pD+ NF C PRE3	87500834 (High voltage)	0.29 W	33.5 W - 200 W	169 V - 355 V	200 mA - 1050 mA	D4i (Internal DALI)	12/05/2021	12/05/2026

SYN_CE423017	Osram	OT DX 40/170-240/1A0 DIMA NFC G2 CE		0.45 W	6 W – 40 W	17 V – 65 V	150 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 40/170-240/1A0 DIMA NFC G2 B CE		0.45 W	6 W – 40 W	17 V – 65 V	150 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 75/170-240/1A0 DIMA NFC G2 CE		0.32 W	17 W – 75 W	35 V – 150 V	150 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 75/170-240/1A0 DIMA NFC G2 B CE		0.32 W	17 W – 75 W	35 V – 150 V	150 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 75/170-240/1A0 DIMA NFC G2 P CE		0.32 W	17 W – 75 W	35 V – 150 V	150 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 110/170-240/1A0 DIMA NFC G2 CE		0.32 W	20 W – 110 W	65 V – 230 V	150 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 110/170-240/1A0 DIMA NFC G2 B CE		0.32 W	20 W – 110 W	65 V – 230 V	150 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 165/170-240/1A0 DIMA NFC G2 CE		0.34 W	30 W – 165 W	95 V – 260 V	150 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 165/170-240/1A0 DIMA NFC G2 B CE		0.34 W	30 W – 165 W	95 V – 260 V	150 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 200/170-240/1A0 DIMA NFC G2 CE		0.33 W	40 W – 200 W	140 V – 300 V	250 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE423017	Osram	OT DX 200/170-240/1A0 DIMA NFC G2 B CE		0.33 W	40 W – 200 W	140 V – 300 V	250 mA – 1050 mA	D4i (Internal DALI)	28/05/2024	28/05/2029
SYN_CE422008	Osram	OT 20/170-240/1A0 4DIM NFC G3 CE		0.2 W	5 W – 22W	10 V – 38 V	150 mA – 1050 mA	DALI2 (External DALI)	23/02/2024	23/02/2029
SYN_CE422008	Osram	OT 40/170-240/0A7 4DIM NFC G3 CE		0.2 W	6 W – 40 W	30 V – 77 V	150 mA – 700 mA	DALI2 (External DALI)	23/02/2024	23/02/2029
SYN_CE422008	Osram	OT 40/170-240/1A0 4DIM NFC G3 CE		0.2 W	6.5 W – 40 W	15 V – 56 V	150 mA – 700 mA	DALI2 (External DALI)	23/02/2024	23/02/2029
SYN_CE422008	Osram	OT 75/170-240/0A7 4DIM NFC G3 CE		0.25 W	17 W – 75 W	50 V – 150 V	150 mA – 700 mA	DALI2 (External DALI)	23/02/2024	23/02/2029
SYN_CE422008	Osram	OT 75/170-240/1A0 4DIM NFC G3 CE		0.25 W	17 W – 75 W	35 V – 115 V	150 mA – 1050 mA	DALI2 (External DALI)	23/02/2024	23/02/2029
SYN_CE422008	Osram	OT 75/170-240/1A5 4DIM NFC G3 CE		0.25 W	15 W – 75 W	25 V – 75 V	350 mA – 1500 mA	DALI2 (External DALI)	23/02/2024	23/02/2029

SYN_CE422008	Osram	OT 110/170-240/1A0 4DIM NFC G3 CE		0.28 W	21 W – 110 W	55 V – 157 V	150 mA – 1050 mA	DALI2 (External DALI)	23/02/2024	23/02/2029
SYN_CE422008	Osram	OT 110/170-240/0A7 4DIM NFC G3 CE		0.28 W	21 W – 110 W	80 V – 220 V	150 mA – 700 mA	DALI2 (External DALI)	23/02/2024	23/02/2029
SYN_CE422008	Osram	OT 165/170-240/1A0 4DIM NFC G3 CE		0.3 W	27 W – 165 W	90 V – 260 V	150 mA – 1050 mA	DALI2 (External DALI)	23/02/2024	23/02/2029
SYN_CE422008	Osram	OT 200/170-240/1A0 4DIM NFC G3 CE		0.3 W	33 W – 200 W	140 V – 300 V	150 mA – 1050 mA	DALI2 (External DALI)	23/02/2024	23/02/2029
SYN_CE424003	MOSO	MOSO U6-040D057		0.42 W	9.5 W – 39.9 W	20 V – 57 V	167 mA – 1050 mA	DALI2 (External DALI)	01/10/2024	01/10/2029
SYN_CE424003	MOSO	MOSO U6-080D115		0.43 W	25 W – 80.3 W	35 V – 115 V	219 mA – 1056 mA	DALI2 (External DALI)	01/10/2024	01/10/2029
SYN_CE424003	MOSO	MOSO U6-120D172		0.46 W	33.5 W – 119.7 W	75 V – 172 V	195 mA – 1050 mA	DALI2 (External DALI)	01/10/2024	01/10/2029
SYN_CE424003	MOSO	MOSO U6-165D236		0.46 W	45.5 W – 157.6 W	105 V – 236 V	193 mA – 1037 mA	DALI2 (External DALI)	01/10/2024	01/10/2029
SYN_CE424003	MOSO	MOSO U6-200D286		0.41 W	59 W – 203.1 W	143 V – 286 V	206 mA – 1069 mA	DALI2 (External DALI)	01/10/2024	01/10/2029
SYN_CE424004	MOSO	MOSO U7-022D072+		0.4 W	5.6 W – 22.1 W	24 V – 72 V	79 mA – 507 mA	D4i (Internal DALI)	01/10/2024	01/10/2029
SYN_CE424004	MOSO	MOSO U7-026D038+		0.42 W	13 W – 26 W	20 V – 38 V	343 mA – 1070 mA	D4i (Internal DALI)	01/10/2024	01/10/2029
SYN_CE424004	MOSO	MOSO U7-032D112+		0.42 W	9.3 W – 32.1 W	45 V – 112 V	84 mA – 504 mA	D4i (Internal DALI)	01/10/2024	01/10/2029
SYN_CE424004	MOSO	MOSO U7-040D057+		0.42 W	14.6 W – 40 W	28 V – 57 V	257 mA – 1069 mA	D4i (Internal DALI)	01/10/2024	01/10/2029
SYN_CE424004	MOSO	MOSO U7-060D096+		0.48 W	17.7 W – 60 W	38 V – 96 V	185 mA – 986 mA	D4i (Internal DALI)	01/10/2024	01/10/2029
SYN_CE424004	MOSO	MOSO U7-060D200+		0.48 W	16.6 W - 60 W	78 V – 200 V	83 mA – 504 mA	D4i (Internal DALI)	01/10/2024	01/10/2029
SYN_CE424004	MOSO	MOSO U7-080D272+		0.48 W	21.7 W – 79.5 W	115 V – 271 V	189 mA – 800 mA	D4i (Internal DALI)	01/10/2024	01/10/2029
SYN_CE424004	MOSO	MOSO U7-120D180+		0.45 W	32.7 W – 120 W	75 V – 180 V	106 mA – 1060 mA	D4i (Internal DALI)	01/10/2024	01/10/2029

SYN_CE424004	MOSO	MOSO U7-120D320+		0.48 W	33.8 W – 120 W	160V – 320 V	106 mA- 695 mA	D4i (Internal DALI)	01/10/2024	01/10/2029
SYN_CE424004	MOSO	MOSO U7-200D300+		0.48 W	47.7 W – 198.9 W	143 V – 300 V	157 mA – 1042 mA	D4i (Internal DALI)	01/10/2024	01/10/2029
SYN_CE423019	OSRAM	OT DX 24 /170-240/0A7 DIMA NFC G2 CE		0.35 W	4 W – 24 W	12 V – 48 V	100 mA – 700 mA	DALI2 (External DALI)	10/12/2024	10/12/2029